

12. Set up for Serial Printer Test.
SW2=4,6,7,8 ON / SW4= 5,8 OFF and set the 2nd CRT for RS232
and 1200 baud.
13. Boot DTOS Rev.03 and run Print X. Select test 2,3,4,5,6,7
and 13. Perform margin testing while it is running.

FINAL STEPS:

1. Set the board as ZETACO Default Configuratrion unless specified by QA.
SW1 = 5,6,7,8 UP (Device code 17).
SW2 = 2,3,4 OFF (T4)
SW3 = 3 ON (R8)
SW4 = 1 thru 6 ON (K7)
SW5 = 1,3 ON (E6)
2. Double_ckeck the power up Self_Test.