

1220 Power Supply

FIRST RESISTANCE READING IS FROM GRD. TO PIN.

SECOND RESISTANCE READING REVERSE LEADS.

U-1

Pin	Resistance
1	INF
2	200Ω - 900Ω
3	30Ω - 7Ω
4	30Ω - 7Ω
5	2.0KΩ - 1.5KΩ
6	1.5KΩ - 1.0KΩ
7	GRD.
8	INF.
9	1.5KΩ - INF.
10	30Ω - 7Ω
11	1.2KΩ - 500Ω
12	600Ω
13	1.5KΩ - 1.0KΩ
14	INF.

U-2

Pin	Resistance
1	INF.
2	750Ω - 650Ω
3	250Ω
4	200Ω
5	2.0KΩ - 1.5KΩ
6	1.6KΩ - 1.0KΩ
7	GRD.
8	INF.
9	1.1KΩ - INF.
10	250Ω
11	1.0KΩ - 650Ω
12	600Ω
13	1.5KΩ - 1.0KΩ
14	INF.

1220 POWER SUPPLY

TAKE FIRST RESISTANCE READING THEN REVERSE LEADS

Q-1	B-E	12 Ω - 500 Ω
TP36	B-C	12 Ω - 250 Ω
	C-E	10 Ω - 800 Ω
Q-3	B-E	12 Ω - 500 Ω
TP4505	B-C	12 Ω - 1.5k Ω
	C-E	125 Ω - 9 Ω
Q-4	B-E	9 Ω
TP4399	B-C	9 Ω - 125 Ω
	C-E	100 Ω - 9 Ω
Q-5	B-E	9 Ω - 12 Ω
TP4399	B-C	9 Ω - 70 Ω
	C-E	80 Ω - 10 Ω
Q-6	B-E	13 Ω - 500 Ω
TP4505	B-E	13 Ω - 1.0k Ω
	C-E	100 Ω - 12 Ω
Q-7	B-E	12 Ω - INF.
TP36	B-C	12 Ω - INF.
	C-E	INF.